Настройка модема Инструкция по настройке

1. Установите драйвера. Убедитесь в том, что модем установлен в Диспетчере устройств.

Мой компьютер→ Управление→ Диспетчер устройств→ Модемы→ SCI USBModem



Кликните правой кнопкой SCI USBModem – Свойства - Расширенные, укажите команды инициализации модема. Meraфoн: AT+CGDCONT=1,"IP","internet" Билайн AT+CGDCONT=1,"IP","internet.mts.ru" MTC AT+CGDCONT=1,"IP","internet.beeline.ru"

SCI USBModem Properties	? ×
General Modem Diagnostics Advanced Driver Details Extra Settings	Please ask your operator for concrete parameter
Extra initialization commands:	
at+cgdcont=1, "IP", "CMNET"	
0.02.01.02.02.03.02.02.03.02.03.02.03.02.0	
Advanced Port Settings	
Change Default Preferences	

Кликните на «Изменить умолчания» и выставьте параметры как на картинке.

SCI USBModem Defa	ult Preferenc	es	? ×
General Advanced			
Call preferences		<u>Balbalbalbalbalbal</u>	
Disconnect a c	all if idle for more	than	mins
Cancel the call	if not connected	l within	secs
Data Connection Pre	eferences		
Port speed:	921600	*	
Data Protocol:		~	
Compression:		~	
Flow control:	None	*	
			General
			Lancel

2. Создайте Dialup подключение

Панель управления - Сетевые подключения - Создать новое подключение - Подключится к Интернет - Установить подключение в ручную









New Connection Wizard
Select a Device This is the device that will be used to make the connection.
You have more than one dial-up device on your computer. Select the devices to use in this connection:
☐ 🧼 Modem - In-Build Conexant ICH AC '97 Modem (COM4) ☑ 🌺 Modem - SCI USBModem (COM5)
< Back Next > Cance



New Connection Wizard		
Internet Account Informa You will need an accour	ation It name and password to sign in to your Internet account.	D
Type an ISP account na safe place. (If you have f	me and password, then write down this information and store it in a forgotten an existing account name or password, contact your ISP.]	l
User name:		
Password:		
Confirm password:		
Use this account na this computer	me and password when anyone connects to the Internet from	
Make this the default Internet connection		
	< Back Next > Cancel	

Connect My	connection 2
<u>U</u> ser name: <u>P</u> assword:	
Save this Me o <u>n</u> Anyon	user name and password for the following users: y e who uses this computer
Djal:	*99***1#
	Cancel Pr <u>o</u> perties <u>H</u> elp

4. Кликните ОК.

Connec	ting My connection	
3	Dialing *99***1#	
	Cancel	